

# G Shape with Inline PTT and Lapel Mic

> ECH1040



## Features

- > Soft, discreet and comfortable
- > Environmental PU cable reinforced with Kevlar
- > Discreet communication in sensitive environments
- > Suitable for many applications including; security personnel, hotel and catering staff, etc

## Technical Specification

### Speaker

Dimensions:	∅5.0mm * 6.0mm
Impedance:	320 ± 14% @ 1000hm
Rated Input Power	100mW
Rated Output Power	300mW
Sound Pressure Level:	105 ± 3db @1000Hz

### Microphone

Type:	Electric Microphone
Impedance:	2.2 kOhm
Sensitivity:	-40 ± 3db @1000Hz (0db = 1V/PA)
Operating Voltage:	1.1-10VDC

### PTT

Dimensions:	34.9 * 14.2 * 11.8mm
-------------	----------------------

**Call us now to find out more: +33 (0)3 80 27 16 38**  
or email us : [contact@mobileteam.fr](mailto:contact@mobileteam.fr)

#### Mobile Team

Centre d'Affaires Dionysos,  
3, rue Jean Monnet  
21300 Chenove - FRANCE  
T: +33 (0)3 80 27 16 38  
E: [contact@mobileteam.fr](mailto:contact@mobileteam.fr)

## > Connectors

	Product Code	Description
	ECH1040 <b>J6</b>	Surveillance two-wire earpiece with acoustic tube with 3.5mm straight Suitable for any radio or speaker Mic with 3.5mm audio jack
	ECH1040 <b>M2</b>	Surveillance two-wire earpiece with acoustic tube with <b>Motorola two pin 2.5mm for T5.</b> Suitable for Motorola T5 series
	ECH1040 <b>M1</b>	Surveillance two-wire earpiece with acoustic tube with <b>Motorola Two-pin right angle.</b> Suitable for Motorola: GP300, CP040, XTN446, HYT: C600.TC610/TC620,TC446
	ECH1040 <b>M1A</b>	Surveillance two-wire earpiece with acoustic tube with <b>Motorola Two-pin right angle.</b> Suitable for Motorola: XTNi and XTNiD
	ECH1040 <b>M4</b>	Surveillance two-wire earpiece with acoustic tube with <b>Motorola multiple pin M4.</b> Suitable for Motorola: GP328, GP340, GP360, GP380
	ECH1040 <b>M5</b>	Surveillance two-wire earpiece with acoustic tube with <b>Motorola multiple pin M5.</b> Suitable for Motorola: GP344, HYT: TC-780, TC3000; Kirisun: PT7200
	ECH1040 <b>M7</b>	Surveillance two-wire earpiece with acoustic tube with <b>MOTOTRBO multiple pin.</b> Suitable for Motorola DP3400/ DP3600
	ECH1040 <b>K1</b>	Surveillance two-wire earpiece with acoustic tube with <b>Kenwood two-pin.</b> Suitable for Kenwood: TK-2100, 2102, 2130, 2160, TK-3100, 3160, TK-3101, TK-3102, TK-3130
	ECH1040 <b>K2</b>	Surveillance two-wire earpiece with acoustic tube with <b>Kenwood Multiple pin.</b> Suitable for Kenwood: TK-280, TK-290, TK-380, TK-385, TK-390, TK-480, TK-481, TK-2041, TK-2140, TK-3140, TK-3148
	ECH1040 <b>S2</b>	Surveillance two-wire earpiece with acoustic tube with <b>Icom two pin right angle.</b> Suitable for Icom: IC-F3G, IC-F3GS, IC-G3GT, IC-F4G, IC-F4GS, ICF4GT, IC-F43GS, C-F43GT, IC-F43TR, IC-F11, IC-F11S, IC-F21, IC-F21S, IC-F31
	ECH1040 <b>S4</b>	Surveillance two-wire earpiece with acoustic tube with <b>Icom multiple pin.</b> Suitable for Icom: IC-F50, IC-F51, IC-F60, IC-F61, IC-F30GS, IC-F3061, IC-F4061, IC-F3162, IC-F4162
	ECH1040 <b>Y2</b>	Surveillance two-wire earpiece with acoustic tube with <b>Yaesu/Vertex Standard One-Pin Right Angle with screw.</b> Suitable for Vertex: VX-10, VX-110, VX-160, VX-180, VX-210, VX-210A, VX-200, VX-300, VX-400, VX-410, VX-420, VX-150, VX-2R
	ECH1040 <b>Y6</b>	Surveillance two-wire earpiece with acoustic tube with <b>Yaesu/Vertex Standard Multiple-Pin.</b> Suitable for Vertex: VX-820, VX-821, VX-824, VX-829, VX-920, VX-921, VX-924, VX-929
No image available	ECH1040 <b>ET1</b>	Surveillance two-wire earpiece with acoustic tube with Entel <b>Entel HX series:</b> HX402/403/405, 412/413/415, 422/423/425, 482/483/485
	ECH1040 <b>T1</b>	Surveillance two-wire earpiece with acoustic tube with Tait <b>Suitable for Tait:</b> TP8110, TP8115, TP8120, TP8135, TP8140, TP7110

### Mobile Team

Centre d'Affaires Dionysos,  
3, rue Jean Monnet  
21300 Chenove - FRANCE  
T: +33 (0)3 80 27 16 38  
E: contact@mobileteam.fr

